

Wireless Pairing & Streaming – Cochlear™ Baha® 5 and ReSound



Maximize your hearing with both ears¹

Microphones

Note: When bimodal pairing, first ensure hearing devices are programmed to opposite ears.

1. Turn off ReSound hearing aid and Cochlear Baha 5 Processor



2. Turn on microphone
Note: Ensure microphone is charged.



3. Locate and press the pairing button on back by the clip



20 seconds

Note: The LED will flash yellow while device is in pairing mode for 20 seconds.

4. Turn on ReSound hearing aid, pause 2 seconds, then turn on Baha 5 Processor



TV Streamers

1. Plug power and audio cables into TV Streamer and connect to audio source



2. Turn off ReSound hearing aid and Baha 5



3. Press pairing button



20 seconds

Note: The LED will flash yellow while device is in pairing mode for 20 seconds.

4. Turn on ReSound hearing aid, pause 2 seconds, then turn on Baha 5 Processor



Microphones and TV Streamers

1. Turn on ReSound hearing aid then Baha 5 Processor
2. Turn on microphone or TV



Streaming to one or both hearing devices

Note: Streaming must be started and stopped on each device individually.

OPTION

- A. Baha 5 Processor

Long-press the upper button on your sound processor once.



OPTION

- B. Baha Remote Control 2

Press the streaming button on this Remote Control.



Streaming button

OPTION

- A. Press and hold the push button on your ReSound Hearing Aid for 3 seconds.



OPTION

- B. Using ReSound Unite Remote

If you have a ReSound Unite™ Remote Control (optional), simply press the streaming button on this Remote Control.



Streaming button

¹ Wolfe, Jace. "Why Two Are Better Than One." Presented at ACIA 2014, Nashville, TN.

Wireless Pairing & Streaming – Cochlear™ Baha® 5 and ReSound



Maximize your hearing with both ears¹

Phone Clip – Pairing with ReSound Hearing Aid or Baha 5

1. Turn off ReSound hearing aid or Baha 5 Processor




2. Turn on Phone Clip and remove silver cap



Note: Phone Clip can not be paired bimodally.

3. Press white pairing button



20
seconds

Note: The LED will flash yellow while device is in pairing mode for 20 seconds.

4. Turn on ReSound hearing aid or Baha 5 Processor



Phone Clip – Pairing with Mobile Phone

Note: The Phone Clip must be paired to a Bluetooth source before it can be used.


1. Turn on Phone Clip and remove silver cap



2. Turn on mobile phone's Bluetooth function

Refer to your mobile phone user guide for instructions.

3. Press blue Bluetooth pairing button



2
minutes

Note: During pairing mode the LED will turn blue.

4. On your mobile phone search for new Bluetooth devices and select "Hearing Aid Phone" from the list.

Note: If your mobile phone asks for a pass code, enter "0000" (four zeros).

Your Phone Clip should now be paired with your mobile phone.

Note: If your mobile phone asks which Bluetooth service you wish to enable, select "Headset".

Phone Clip – Managing Calls

Incoming calls:

To answer a call, press once.

To decline a call, double-click.

During a call:

To transfer a call started on your phone to the phone clip, press once

To put a call on hold, press and hold for 2 seconds.

To make a call:

To redial the last number, double-click.

To activate voice dialling, press and hold for 2 seconds.



Phone Clip – Streaming Music

Connect the device to the Phone Clip using Bluetooth.

Start playing music on the device.

You hear the audio streaming from the device.

To stop streaming, stop playing music on the device.



Tip! Use the volume controls on the Phone Clip to change the volume on your hearing aid.



Cochlear®

ReSound

©Cochlear Limited 2016. All rights reserved. Hear now. And always and other trademarks and registered trademarks are the property of Cochlear Limited or Cochlear Bone Anchored Solutions AB. The names of actual companies and products mentioned herein may be the trademarks of their respective owners.
© 2016 GN ReSound A/S. All rights reserved.
ReSound is a trademark of GN ReSound A/S.



¹ Wolfe, Jace. "Why Two Are Better Than One." Presented at ACIA 2014, Nashville, TN.